

# D421-LED

## 14" Decorative Round Luminaire

# Installation Guide



## IMPORTANT SAFETY INSTRUCTIONS

1. Read carefully before installing fixture. Retain for future reference.

**⚠ WARNING** To prevent electrical shock, turn off electricity at fuse box before proceeding.

2. Failure to follow instructions may result in serious injury or death.

3. Upon receipt the fixture, thoroughly inspect for any freight damage which should be brought to the attention of the delivery carrier. Compare the catalog description listed on the package slip with the fixture label on the housing to assure you have received material.

4. This fixture must be wired in accordance with the international electrical code and applicable local codes and ordinances. Proper grounding is required to insure personal safety. Carefully observe the correct grounding procedure under installation section.

5. Before starting the installation and servicing, disconnect the power by turning off the circuit breaker. Turning the power off by using the light switch is not sufficient to prevent electrical shock. All work should be done by a qualified electrician. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

\*Deco Digital assumes no responsibility for claims arising out of improper or careless handling or installation of this product.

## INSTALLATION

When a recessed junction box is used:

1. Turn off power to the circuit.
2. Open luminaire by removing six (6) screws from the front.
3. Drill out holes in the rear housing to be used with the junction box.
4. Feed wires (hot, neutral, ground, dim+, dim- if needed) through the center hole on the back housing, and fasten back housing to the junction box.
5. Make electrical connections.
6. Close luminaire and re-fasten the six screws.
7. Energize circuit.

When surface mount conduit is used:

1. Turn off power to the circuit.
2. Open luminaire by removing six (6) screws from the front.
3. Drill out holes in the rear housing for fastening luminaire to the wall.
4. Using the rear housing as a template, mark the location on the wall to install anchors.
5. Drill holes and install anchors in wall.
6. Fasten rear housing to wall.
7. Open conduit opening in the front housing of the luminaire.
8. Attach conduit. Make wire connections.
9. Close luminaire using the six screws from step 2.
10. Energize circuit.

*Deco Lighting practices a program of continuous product improvement, and as a result product specifications change frequently. We reserve the right to change product specifications without notice. Contact Deco for the latest product information.*